



Explosion Proof EF24 Transmitter (only) 12 Buttons 2 Speed

Características Esenciales

- 1 Años de Garantía, Partes y Servicios Disponibles en América

Especificaciones Técnicas

Codigo FCC	OFNF21	Rango de Frecuencia	VHF: 310~331 MHz; UHF: 425 ~ 446 MHz
Fuente de Alimentación del Transmisor	4 AA batteries	Parada de Emergencia	Yes
Material	Glass-Fiber PA	Rango de temperatura de Trabajo	-40 ~ 185 °F / -40 ~ 85°C
Distancia de Control	300 ft up to 600 ft with optional antenna	Normas	FCC and OSHA standard 1910.179
Código de Seguridad	32 bits (4.3 billion)	Garantía	1 Year
Potencia del Transmisor	≤10dBm		

EF-24 TRANSMITTER

Explosion-proof design



MODEL: EF24-TX
ITEM CODE: 924-400-001
Dimension: 186 x 61 x 51 mm
Weight: 280g (without batteries)



Product features


- 10 double steps pushbuttons + EMERGENCY STOP + START KEY + SPARE
- 20 control contactors
- Battery voltage warning device, the power supply is cut off during low power
- Safety key switch is to prevent from unauthorized users
- Program the button function by computer interface
- Up/down, east/west, south/north can be programmed to to interlock or non-interlock
- Start key can be programmed to start, toggle switch, normal or other functions
- The spare buttons can be programmed to start, toggle, interlock or normal, etc

Standard Configuration

- One transmitter (with hanging belt)
- One dust bag
- One receiver
- Receiver is with 1.6 meter cable
- Battery: one pair
- One receive antenna
- Operation and maintenance manual

Dual power supply:

EF24 is new series explosion-proof radio remote control based on F24 series, strictly complies with explosion-proof criterion GB3638.1 and GB3836.4, and has passed EXiB1 BT4 intrinsic safety certification, can operate safely in the chemical and petrochemical industries, mining and other flammable, explosive and hazardous environments,



Peso & Dimensiones

Peso Total

1 lbs / 1 Kg

Referential Images / Imágenes Referenciales

Specifications may change without notice / las especificaciones pueden cambiar sin previo aviso