



## Radio Remote Control 2 Channels 2 Speed Multi voltage Range 300 ft

### Características Esenciales

- 200 Auto Channels replacing traditional single channel quartz plus 1 Million ID Codes.
- Easy Pairing System, no need of software or copier to add or replace lost or broken Transmitter
- Customizable 200 Functions settings to meet any special requirements
- Reinforced fiber plastic case for Transmitter and Receiver plus rubber protector for Transmitter
- 1 Años de Garantía, Partes y Servicios Disponibles en América

## Especificaciones Técnicas

|                                       |                 |                                 |                                |
|---------------------------------------|-----------------|---------------------------------|--------------------------------|
| Codigo FCC                            | 2AZMK-Q1212     | Código de Seguridad             | 200 Millions                   |
| Wireless Control IP Protection        | IP65            | Potencia del Transmisor         | ≤10dBm                         |
| Botones                               | 3               | Rango de Frecuencia             | 433/480 MHz                    |
| Fuente de Alimentación del Transmisor | 2 AA batteries  | Parada de Emergencia            | YES                            |
| Material                              | PA6 30% GF      | Rango de temperatura de Trabajo | -40 ~ 185 °F / -40 ~ 85°C      |
| Fuente de Alimentación del Receptor   | AC 110V-480V    | Normas                          | FCC and OSHA standard 1910.179 |
| Sensibilidad del Receptor             | dBm -112        | Garantía                        | 1 Year                         |
| Distancia de Control                  | 300 ft / 100 mt |                                 |                                |

## Peso & Dimensiones

**Peso Total** 4 lbs / 2 Kg

## Detalles del Empaque

**A Altura Total** 5.3"

**W Ancho** 2.7"

**D Depth** 1.2"

Referential Images / Imágenes Referenciales  
Specifications may change without notice / las especificaciones pueden cambiar sin previo aviso